



LED 2-Pin PL Magnetic Ballast Compatibility Chart

Ballast Brand*	Part Number	# Of Lamps	Voltage	Lamp Connection	1 Lamp		2 Lamps		Target Lamp Type
					120V	277V	120V	277V	
Philips Advance	VH-1B13-TP-W	1	277	NA	NA	P,T	NA	NA	1*13W
Philips-Advance	H-1B13-TP-W	1	120	NA	NA	P,T	NA	NA	1*13W
Philips-Advance	VH-2Q26-TP-BLS	2	277	NA	NA	NA	NA	✓	2*26W
Philips-Advance	VLO-2S13-TP	2	277	NA	NA	P	NA	P	2*13W, 1*26W
Philips-Advance	VLO-13-TP	1	277	NA	NA	P	NA	NA	1*13W, 1*26W
Robertson	HP2627P	1	277	NA	NA	P,T	NA	NA	1*26W
Robertson	HP22627P	2	277	Parallel	NA	NA	NA	P,T	2*26W
Robertson	S1P	1	120	NA	P	NA	NA	NA	1*13W
Robertson	O1527P(3P10104)	2	277	NA	NA	P	NA	P	2*13W, 1*26W, 1*13W
Robertson	HP2265P(3P10085)	2	120	Series	NA	NA	T	NA	2*26W
Robertson	HP213P(3P10073)	2	120	Series	NA	NA	P,T	NA	2*13W
Robertson	HP28P	1	120	NA	P	NA	NA	NA	1*26W
Robertson	HP18P	1	120	NA	P,T	NA	NA	NA	1*18W
Robertson	HP218SP	2	120	Series	NA	NA	P,T	NA	2*18W

Applies to the
following Satco products:

S9862, S9863, S9864, S9865

F Flicker after >2s start-up (**NC**)
N Acoustic noise >20dB
P PF <0.85
T THD >30%
NC Not compatible
NA Not applicable

This list is current as of May. 2018. We are continuously testing for compatible ballasts. Please check back for updates.

* All trademarks are the property of their respective owners

110 Heartland Blvd.
Brentwood, NY 11717
PH 631-243-2022
FX 631-243-2027

Distribution Centers
New York, Florida,
Texas, Washington,
California, Puerto Rico

National Toll-Free
800-43-SATCO
(800-437-2826)
www.satco.com

Copyright© 2018
Satco Products, Inc.
All Rights Reserved.
Rev: May 29, 2018